

# Elite 3 Hot Tub Installation Information



213cm x 213cm x 92cm

## Access

You will require a clear run of at least 95cm wide and 2.4 metres high for us to get your new hot tub in position. If you have any 90 degree turns or steps please send photos of these to [technical@grizzlybearhottubs.co.uk](mailto:technical@grizzlybearhottubs.co.uk)

## Electrical Supply

A 13amp plug and play hot tub will require a RCD protected socket to be situated around 3 metres away from your hot tub. The hot tub will come complete with a cable and plug attached, ready to plug in

A 32amp power supply will require a RCD protected cable with a type C breaker to be run to a commando socket located around 3 metres away from your hot tub. We also require the commando plug to be pre wired to a 6mm 3 core SY Flex cable with UV protection (or supply flexible conduit) leaving an 8 metre tail. This extra long tail is to allow for the perfect siting of your hot tub

## Cable Entry

The cable can enter at any corner and run inside the cabinet or if you would like to bring the cable through the base of the hot tub please use the sizes we have given above to ensure the cable does not hit any components.

## Cover Lifter

The cover lifter can open to any side you like. Please ensure you leave 55cm clearance at the side that you would like your cover to open to.